>



PRODUCT NUMBER: 1010923 Leightning L2s Headband Earmuff

Learn more about our products at howardleight.com



Q

Overview
Reference Number 1010923
Product Type Hearing Protection
Range Earmuffs
Line Noise Blocking Earmuffs
Brand Howard Leight by Honeywell
Brand formerly known as BILSOM
Industry
 Industry • Administration • Agriculture • Army - Defence • ATEX environment Automotive and Part Manufacturer • Aviation Chemical Industries • Energy or Electricity Foundry • Glass Industries • Green Spaces • Homeland defense Iron and steel industry • Laboratory • Logistics • Maintenance • Medical and Pharmaceutical Metal steel • Minning and Quarrying • Offshore • Paper Industries • Petro-chemical

Printing Industries
 Services
 Ship Building
 Telecoms
 Textile Industries
 Transportation

Utilities
 Water treatment
 Welding
 Wood Industries

Product Use

Noise Blocking Earmuff

Features & Benefits

Feature

AIR FLOW CONTROL TECHNOLOGY Bilsom's patented Air Flow Control[™] technology delivers optimal attenuation across all frequencies, without increasing earcup size or weight. A patented baseplate chamber and high-tech non-woven layer manage the flow of air inside the earmuff to control how sound reaches the ear. The result is better, more consistent

Page 1 Of 3 © Honeywell International Inc.

Leightning L2s Headband Earmuff - 1010923

overall attenuation for virtually all industrial noise environments. STEEL WIRE CONSTRUCTION Robust steel headband withstands demanding use, especially in tough environments. SNAP-IN EAR CUSHIONS Snap-in ear cushions make replacement quick and easy. PADDED FOAM HEADBAND delivers long-wearing comfort with minimal pressure on the head.

Benefit

When you're in a tough industrial environment and need to block noise, Bilsom's Leightning series' steel wire construction provides high performance and robust durability. Leightning stands up to daily use and abuse without compromising comfort. Bilsom has optimized the Leightning series to deliver the highest level of comfort available, featuring an exclusive padded foam headband and super soft ear cushions that eliminate that "squeezing pressure" on the head.

Technical Description

SNR (dB) 31
H (dB) 31
M (dB) 29
L (dB)

23

Attenuation Data

Frequency (Hz) Frequenz (Hz) Fréquence (Hz)	63	125	250	500	1000	2000	4000	8000
Mean Attenuation (dB) Mittlere Dämmung (dB) Atténuation moyenne (dB)	20.0	20.1	24.5	29.3	34.4	32.4	35.9	35.6
Standard Deviation (dB) Standardabweichung (dB) Déviation standard (dB)	4.5	4.0	2.9	3.2	2.6	3.0	2.6	3.2
Assumed Protection (dB) Angenommener (dB) Protection supposée (dB)	15.5	16.1	21.6	26.1	31.8	29.4	33.3	32.4

Earmuff Construction

Metal

Other Material

Steel Wire, PUR-E, PVC, Textile, PC/PBT, ABS

Dielectric

No

Color BlackHeadband and Dark Grey Cup

Batteries Needed

None

```
Weight (grs)
222
```

Headband Style

Over-Head

Sound Amplification

AM/FM Radio

No

Automatic Shut-Off Function

Audio Input Jack

No

Hi-Visibility

No

Certifications

EC Category PPE 2

Quality Assurance ISO 9001 / 2000

EC Certificate Number EC1285

EC Attestation EC Attestation

EC Attestation Number 041198

Maintenance

Life Cycle

Cushions should be replaced periodically to retain maximum attenuation. Use the following as a guideline for replacement of ear cushions and insert foam. General use and wear - Ear cushions and foam inserts should be replaced at least every 6 months. Heavy use or wear in humid/extreme climates - Ear cushions and foam inserts should be replaced at least least every 3 months. Cracking or leakage is visible - replace ear cushions and foam inserts immediately.

Storage Information

When not in use, the earmuffs should be stored in a clean dry container or locker. Do not use solvents or petroleum-based products. Do not immerse the earmuffs in water.

Care Instructions

Earmuffs are an important safety product and should be inspected regularly. Its use, care and maintenance are critical to its effective performance. Earmuffs and in particular ear cushions may deteriorate with use and should be examined at frequent intervals for cracking and leakage. If the ear cushions become hard, damaged or deteriorated, they should be replaced promptly using recommended Hygiene Kits. Earmuffs should be maintained by regular cleaning. Use a mild disinfectant solution. A gentle wipe is all that is required.

Parts & Accessories

Accessories

Hygiene Kit - Packed in a plastic bag, including two ear cushions and two foam pads. Ref. # 1011999 for L2, L2N, L2F Beltclip - For carrying purpose. Old Ref. # 1000252 New Ref. # 1016730 Cool II Pads - Sweat absorbing pads. Ref. # 1000365 5-pair, Ref. # 1000364 100-pair

Optisorb - cotton sleeve slides over earcup. Ref. # 3302101 Polar Hood - Ref. # 1016870 Lg/XLg; Ref. # 1016871 Sm/Med

Packaging

EAN Code 7312550109236

© Honeywell International Inc.